

[ Close Window ] [ Print Window ]

## Tests 1 - 2

TEST	ACTION	APPLICABILITY
1	<p><b>NOTE: Determine if the DTC is set by the ECM (CM551) or the PCM (JTEC).</b></p> <p>Turn the ignition on.</p> <p>Is this DTC set by the ECM?</p> <p>Yes → Go To 2</p> <p>No → Go To 7</p>	All
2	<p>Turn the ignition off.</p> <p>Disconnect the APP Sensor harness connector.</p> <p>Turn the ignition on.</p> <p>Measure the voltage between the APP Sensor 5-volt Supply circuit at the APPS harness connector and the engine block (ground).</p> <p>Is the voltage above 4.5 volts?</p> <p>Yes → Go To 3</p> <p>No → Go To 6</p>	All